

PCTWORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau**AA****Giardina 3-12-1****Serial No.: 09/928628****Filing Date: 8/13/01**

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)


(51) International Patent Classification 7 : H03F 1/32	A1	(11) International Publication Number: WO 00/70750
		(43) International Publication Date: 23 November 2000 (23.11.00)

(21) International Application Number: PCT/US00/13130

(22) International Filing Date: 12 May 2000 (12.05.00)

(30) Priority Data:
09/312,353 14 May 1999 (14.05.99) US(71) Applicant: HARRIS CORPORATION [US/US]; 1025 West
Nasa Boulevard, Melbourne, FL 32919 (US).(72) Inventor: TWITCHELL, Edwin, Ray; 4041 Ross Avenue, San
Jose, CA 95124 (US).(74) Agent: NIYOGI, Bidyut, K.; Transnational Enterprises, Inc., 95
Bulldog Boulevard, Suite 207, Melbourne, FL 32901 (US).(81) Designated States: AE, AL, AM, AT, AU, AZ, BA, BB, BG,
BR, BY, CA, CH, CN, CR, CU, CZ, DE, DK, DM, EE, ES,
FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE,
KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD,
MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD,
SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ,
VN, YU, ZA, ZW; European patent (AT, BE, CH, CY, DE,
DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).**Published***With international search report.**Before the expiration of the time limit for amending the
claims and to be republished in the event of the receipt of
amendments.*

(54) Title: BROADCAST TRANSMISSION SYSTEM WITH SINGLE CORRECTION FILTER FOR CORRECTING LINEAR AND NON-LINEAR DISTORTION

**(57) Abstract**

A digital broadcast transmission system (60), comprising a power amplifier (66) that amplifies an information signal to a power level to excite an antenna to emit a broadcast signal. An amplification processing circuitry (68, 70) processes the signal. The information signal is bandpass filtered. The power amplifier (66) causes non-linear distortion to the information signal. The processing circuitry (68, 70) causes linear distortions to the information signal. A single, memoryful filter (76) pre-distorts the information signal to compensate for all of the linear and non-linear distortions. The memoryful filter (76) is a volterra filter. A memoryful filter (112) pre-distorts an information signal to compensate for linear distortion from a power amplifier (102) and non-linear distortion from pre-amplification processing circuitry (104). Linear distortion from post-amplification processing circuitry is compensated by a linear equalizer (114).

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
EA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

BROADCAST TRANSMISSION SYSTEM WITH SINGLE CORRECTION FILTER FOR CORRECTING LINEAR AND NON-LINEAR DISTORTION

The present invention relates to broadcast transmission systems and is particularly directed to compensation of distortion within a digital transmission system, such as a digital TV ("DTV") transmission system.

A high-speed broadcast transmission system such as a DTV broadcast system includes components that distort an information signal away from intended values. Specifically, the system includes a power amplifier that imposes non-linear distortion upon the signal, as a signal is amplified. Also, the broadcast transmission system includes filters, such as band-limiting filters, that impose linear distortion upon the information signal as the signal is filtered.

As a result of such distortions within the transmission system, instantaneous amplitude variations (AM/AM) and instantaneous phase variations (AM/PM) occur. In addition, frequency dependent amplitude and phase variations occur. It is to be appreciated that within a phase-amplitude modulated system, integrity of amplitude and phase must be preserved for optimum system performance.

There is a need for a high-speed technique for adaptive correction of linear and non-linear distortion within a digital broadcast transmission system.

The present invention includes a digital broadcast transmission system comprising signal provision means for providing an electrical information-conveying signal, antenna means for emitting a broadcast signal that conveys the contents of the information signal, amplifier means for amplifying the information signal to a power level suitable to excite said antenna, means to emit the broadcast signal, said amplifier means causing non-linear distortion to the information signal, signal processing means for processing the information signal, including filter means for filtering the information signal, said signal processing means causing linear distortion to the information signal, and a single corrector for pre-distorting the information signal to compensate for the linear and non-linear distortions.

Conveniently, the present invention provides a digital broadcast transmission system. The system includes a signal provision means for providing an electrical information-conveying signal. Antenna means emits a broadcast signal that contains the contents of the information signal. Amplifier means amplifies the information signal to a power level suitable to excite the antenna means to emit the broadcast signal. The amplifier means causes non-linear distortion to the information signal. Signal processing means processes the information signal. The signal

processing means causes linear distortion to the information signal. A single filter pre-distorts the information signal to compensate for the linear and non-linear distortions.

Advantageously, the present invention also provides a digital broadcast system that includes signal provision means for providing an electrical information-conveying signal along a signal stream. Antenna means, located at the end of the signal stream, emits a broadcast signal that conveys the contents of the information signal. A plurality of components is located along the signal stream between the signal provision means and the antenna means. The plurality of components causes distortion to the information signal. At least one of the plurality of components causes linear distortion to the information signal and at least one of the plurality of components causes non-linear distortion to the information signal. A single filter pre-distorts the information signal to compensate for all of the distortion caused by the plurality of components.

The invention also includes a method of transmitting a broadcast signal from a digital transmitter, said method comprising providing an information signal in digital format, converting the information signal to analog format, amplifying the analog information signal, said step of amplifying includes causing non-linear distortion to the information signal, filtering the analog information signal prior to said step of amplifying, said step of filtering prior to amplifying includes causing linear distortion to the information signal, filtering the analog information signal after said step of amplifying, said step of filtering after amplifying includes causing linear distortion to the information signal, and correcting the linear and non-linear distortion in a single corrector.

The present invention will now be described, by way of example, with reference to the accompanying drawings in which:

Fig. 1 is a function block diagram of components of a portion of a transmission system configured to provide one approach to distortion correction;

Fig. 2 is a function block diagram of components of a portion of a transmission system configured to provide distortion correction in accordance with the present invention;

Fig. 3 is the transmission system that includes the structure of Fig. 2;

Fig. 4 is a diagram illustrating a manner in which the structure of Fig. 2 determines and adapts correction;

Fig. 5 is a diagram similar to Fig. 2, but shows another example of system components configured to provide distortion correction in accordance with the present invention; and

Fig. 6 is an expanded block diagram of components in the system for Fig. 5.

Fig. 1 is a function block diagram of components of a portion of a digital broadcast

transmission system 10 that employs one technique of correction for linear and non-linear distortion. The present invention is an improvement over the correction technique of Fig. 1.

In Fig. 1, a plurality of components of the system 10 is located sequentially along a data stream path 12. The data stream is for an information data signal that is transmitted at a relatively high rate. Further, the data signal typically has a relatively wide band (i.e., 18 MHz).

The high data rate and bandwidth are related to the type/environment of the system 10. Specifically, the system 10 is a high definition ("HD") digital television ("DTV") system. The system 10 includes a power amplifier 14, pre-amp signal processing circuitry (i.e., filters and/or the like) 16, and post-amp signal processing circuitry (i.e., filters and/or the like) 18. The power amplifier 14 and the processing circuitry 16, 18 operate in analog format and at a frequency suitable for radio broadcast transmission from an antenna 20. For example, the broadcast signal output from the antenna 20 is at amplification power level of 50 kilowatts and is in the ultrahigh frequency range (300-3000 MHz), and is preferably in the range of 470-860 MHz.

The power amplifier 14 may be comprised of an array of amplifying devices. If a plurality of amplifying devices is present, the power amplifier 14 includes a suitable combiner device. The processing circuitry 16, 18 include such components as bandpass filters. In particular, the post-amp processing circuitry 18 includes a high-power bandpass filter.

Non-linear distortion is imposed upon the information signal by the power amplifier 14 during amplification of the information signal. Specifically, the non-linear distortion is directed to changes in instantaneous amplitude and phase variations. The processing circuitry 16, 18, and in particular the bandpass filters of the processing circuitry, impose linear deformation upon the information signal. Thus, in the sequence of the pre-amp processing circuitry 16, the power amplifier 14, and the post-amp processing circuitry 18, a sequence of linear distortion, non-linear distortion, and linear distortion is imposed upon the information signal as the signal proceeds toward the antenna 20.

In the system 10 of Fig. 1, each of the three distortions (i.e., linear, non-linear, and linear) is corrected or compensated for separately. Specifically, the system 10 includes a first linear equalizer 22 that compensates (i.e., pre-distorts) for the linear distortion caused by the post-amp processing circuitry 18. A non-linear corrector 24 compensates for the non-linear distortion caused by the power amplifier 14. A second linear equalizer 26 compensates for the linear distortion caused by the pre-amp processing circuitry 16.

The three compensating components 22-26 are located sequentially along the data stream 12 of the system 10, and are located upstream of the distortion causing components (i.e., the power amplifier 14 and the processing circuitry 16, 18). The compensating components 22-26

operate in digital format. A digital-to-analog converter (DAC) 28 and an upconverter 30 are located along the signal stream between the group of compensating components 22-26 and the group of distortion causing components 14-18.

Compensation provided by each of the compensating component 22-26 is changeable (i.e., adaptable). Each compensating component 22-26 requires a separate determination in order to accomplish the change of compensation (adaptation of the pre-distortion). Accordingly, three determination function blocks 32-36 are present within the system. The first determination function block 32 determines the pre-distortion that is to be provided by the first linear equalizer 22. The first determination function block 32 is operatively coupled to receive the input 38 for the first linear equalizer 22 and to receive the output 40 of the post-amp processing circuitry 18.

The second determination function block 34 determines the pre-distortion that is to be provided by the non-linear corrector 24. The second determination function block 34 is operatively coupled to receive the input 42 of the non-linear corrector 24 and to receive the output 44 of the power amplifier 14. The third determination function block 36 determines the pre-distortion that is to be provided by the second linear equalizer 26. The third determination function block 36 is operatively coupled to receive the input 46 of the second linear equalizer 26 and to receive the output 48 of the pre-amp processing circuitry 16.

Three separate compensation "steps" are present. Each step of compensation requires sampling signal values, determining needed adaptation, and applying the determined adaptation. Associated with each compensation "step" is a need for appropriate processing capability, memory storage capability, and the like.

The function block diagram of Fig. 2 shows details of a portion of a system 60 that incorporates the present invention. An overview of the complete system 60 is shown in Fig. 3. The components shown in Fig. 2 are located within an 8VSB exciter 62 and transmitter 64 of the system 60 shown within Fig. 3.

The components shown in Fig. 2 include a power amplifier 66, pre-amp signal processing circuitry 68, post-amp signal processing circuitry 70, a DAC 72, and an upconverter 74. In one example, the components 66-74 of the system 60 of Fig. 2 are identical to the corresponding components 14-18, 28 and 30 of the system 10 of Fig. 1.

In distinction from the system 10 of Fig. 1, the system 60 of Fig. 2 includes a non-linear memoryful filter 76 instead of the sequence of the first linear equalizer 22 (Fig. 1), the non-linear corrector 24, and the linear equalizer 26. Preferably, the non-linear memoryful filter 76 is a volterra filter. The single volterra filter 76 is an adaptive filter that corrects for both linear and

non-linear distortion of the downstream components (i.e., the power amplifier 66 and the processing circuitry 68, 70). The volterra filter 76 is modeled by a polynomial.

In order to determine adaptation, a determination function block 78 is operatively connected to receive the input 80 of the volterra filter 76 and the output 82 of the post-amp processing circuitry 70. Accordingly, it is to be appreciated that only a single compensation "step" is present. Further, it is to be appreciated that within the single "step" of compensation, only one group of sampling signal values is needed, only one determination regarding adaptation is needed, and only one application of the determined adaptation is needed.

The system 60 may have various types of components, such as solid-state, tube, etc. The volterra filter 76 can be configured to operate within any of such variation of the system 60.

Fig. 4 is a block diagram that shows the determination of compensation and adaptation of the volterra filter 76. Specifically, within Fig. 4, the distortion causing components (i.e., the power amplifier and the processing circuitry) 66-72 are condensed into a single block located downstream of the volterra filter 76. The output 82 from the distortion causing components 66-72 and the input 80 are provided to the determination function block 78. Within the determination function block 78, the input 80 that is provided to the volterra filter 76 is provided as a first input to a comparison circuit 88 (i.e., a SUM circuit having an addition input and a subtraction input).

A non-linear memoryful filter 90 receives the output signal 82 from the distortion causing components and outputs a signal 92 to the comparison circuit 88. An output 94 of the comparison circuit 88 is termed an error signal and is indicative of the amount of distortion (both linear and non-linear) that occurs along the data stream. Thus, the error signal 94 is indicative of the amount of distortion caused by the distortion causing components 66-74. The error signal 94 is provided as an input to the non-linear memoryful filter 90. The non-linear memoryful filter 90 determines an amount of correction necessary to reduce the error signal to zero or effectively zero (i.e., a null condition). Once the prescribed error value is reached, filter coefficients are downloaded to the volterra filter 76.

To initiate the process of determining the distortion caused by the distortion causing components 66-74, the volterra filter 76 is initially disabled or turned OFF. The "OFF" state of the volterra filter 76 is represented by the switch 96 and bypass line 98 that extends around the volterra filter 76. Accordingly, the output from the distortion causing components 66-72 does not include any pre-distortion imposed by the volterra filter 76, and only includes distortion caused by the distortion causing components. Once the non-linear memoryful filter 90 of the determination function makes an initial determination regarding distortion values, the non-

linear memoryful filter 90 is downloaded to the volterra filter 76 and the switch 96 is set such that the volterra filter 76 is no longer by-passed (the volterra filter is turned ON). Additional adaptation requires this sequence to be repeated.

The use of the switch 96 to initially by-pass the volterra filter 76 may be omitted such that adaptation is initially based upon the use of the volterra filter 76. The advantage of the use of the non-linear memoryful filter 90 (i.e., an off-line approach) is that coefficients can be adapted in groups, and the entire memory space can be used. An in-line compensator approach requires the memory to be reset or loaded again after each volterra kernel update.

Another example of a system 100 in accordance with the present invention is shown in Fig. 5 (only the pertinent portion of the system 100 is shown in Fig. 5). The system 100 of Fig. 5 is similar to the system 60 of Fig. 2. Specifically, the components of the system 100 of Fig. 5 may be part of the overall system shown in Fig. 3. Further, the system 100 of Fig. 5 includes the components of a power amplifier 102, pre-amp processing circuitry 104, post-amp processing circuitry 106, a DAC 108, and upconverter 110.

The system 100 of Fig. 5 differs from the system 60 of Fig. 2, in that only the linear distortion of the pre-amp processing circuitry 104 and the non-linear distortion of the power amplifier 102 are corrected within a volterra filter 112 located upstream of the DAC 108. The linear distortion caused by the post-amp processing circuitry 106 is corrected via pre-distortion within a linear equalizer 114 located upstream of the volterra filter 112.

A determination function block 116 for the volterra filter 112 is connected to an input 118 of the volterra filter 112 and is connected to an output 120 of the power amplifier 102. A determination function block 122 for the linear equalizer 114 is operatively connected to the input 124 of the linear equalizer and the output 126 of the post-amp processing circuitry 106. Compared to the system 10 shown in Fig. 1, the system 100 of Fig. 5 includes one less "step" of compensation (i.e., sampling, adaptation determination, and pre-distortion). Specifically, the functions of compensation performed by the non-linear corrector 24 (Fig. 1) and the second linear equalizer 26 of the system 10 of Fig. 1 are performed by the volterra filter 112 (Fig. 5) of the system 100.

The use of the linear equalizer 114 upstream of the volterra filter 112 has certain benefits, especially if the post-amp processing circuitry 106 includes a high-power filter. The high-power filter may be a relatively high order filter. As such, it requires a significant order of volterra filter to compensate for it. In general, the order of a volterra-type filter will increase as the square of the system order. Whereas, a linear equalizer is typically about the same order as the system for which it compensates. Therefore, if the high-power filter is compensated by linear

filter means external to the volterra filter, it may reduce system cost by allowing a much lower order volterra filter.

Also, the high-power filter attenuates (eliminates) the high order non-linear information needed for non-linear equalizer compensation. Although the information may still be there, it will be sufficiently attenuated so that very high dynamic ranges would be required of the system to provide equalization. Rather than burden the non-linear equalizer with the difficulties of high dynamic range issues, it is prudent to pick-off the return signal before the high-power filter.

A more detailed representation of the system 100 of Fig. 5 is shown in the function block diagram of Fig. 6. Specifically, a Nyquist filter 130 of the 8VSB exciter provides the information signal in a digital and complex format to a complex-to-real converter 132. The output of the complex-to-real converter 132 is a digital signal in real format that is provided as the input to the linear equalizer 114. The linear equalizer 114 is a digital filter that has suitable structure for pre-compensating or pre-equalizing the information signal to compensate for the linear distortion caused by the high-powered filter 134. The linear equalizer 114 may be comprised, or include, a microprocessor that performs a process and/or may be comprised of, or include, discrete "hard-wired" circuitry.

The information signal passes from the linear equalizer 114 to the volterra filter 112. The volterra filter 112 may have any suitable structure for pre-distorting (e.g., pre-equalizing) the signal to compensate for both the non-linear distortion caused by a power amplifier 102, and pre-amp linear distortion. The volterra filter 112 may be comprised of, or include, a microprocessor that performs a program process and/or may be comprised or include, discrete "hard-wired" circuitry.

In the example of Fig. 6, the pre-amp processing circuitry 104 and upconverter 110 includes a first upconverter 136 driven by a first local oscillator 138, a first bandpass filter 140, a second upconverter 142 driven by a second local oscillator 144, a second bandpass filter 146, and a third bandpass filter 148. In addition a fourth bandpass filter 150 is located just downstream of the power amplifier 102. The volterra filter 112 also corrects the distortion from the fourth bandpass filter 150.

The output of the volterra filter 112 is provided to an interpolation component 152. Preferably, the interpolation that occurs is a factor of two. The DAC 108 receives the output of the interpolation component 152 and provides the signal to the first upconverter 136.

For the adaptation of the volterra filter 112, the sample 120 is taken after the power amplifier 102 and after the fourth bandpass filter 150, but prior to the high-power filter 134.

Along the path of the sample is located a first down-converter 154, a first low-pass filter 156, a second down-converter 158, and a second low-pass filter 160. Additionally, an analog-to-digital converter (A/D) 162 and a decimation (i.e., by two) function component 164 are located to provide the input to the correction determination function block 116 for the volterra filter 112.

5 The sample 126 for the linear equalizer correction determination 122 for the linear equalizer 114 is operatively connected to the output of the high-power filter 134. Similar to the sample path for the volterra filter correction determination 116, the path for the linear equalizer correction determination 122 includes suitable components 168 for down-converting, filtering, decimation, and the like.

10 A digital broadcast transmission system (60), comprising a power amplifier (66) that amplifies an information signal to a power level to excite an antenna to emit a broadcast signal. An amplification processing circuitry (68, 70) processes the signal. The information signal is bandpass filtered. The power amplifier (66) causes non-linear distortion to the information signal. The processing circuitry (68, 70) causes linear distortions to the information signal. A
15 single, memoryful filter (76) pre-distorts the information signal to compensate for all of the linear and non-linear distortions. The memoryful filter (76) is a volterra filter. A memoryful filter (112) pre-distorts an information signal to compensate for linear distortion from a power amplifier (102) and non-linear distortion from pre-amplification processing circuitry (104). Linear distortion from post-amplification processing circuitry is compensated by a linear
20 equalizer (114).

Claims:

1. A digital broadcast transmission system comprising signal provision means for providing an electrical information-conveying signal antenna means for emitting a broadcast signal that conveys the contents of the information signal, amplifier means for amplifying the information signal to a power level suitable to excite said antenna means to emit the broadcast signal, said amplifier means causing non-linear distortion to the information signal, signal processing means for processing the information signal, including filter means for filtering the information signal, said signal processing means causing linear distortion to the information signal, and a single corrector for pre-distorting the information signal to compensate for the linear and non-linear distortions.
2. A system as set forth in claim 1, wherein said single corrector is a volterra filter, and in which said filter means includes a pre-amp filter located upstream of said amplifier means and a post-amp filter located downstream of said amplifier means, said pre-amp filter, said amplifier means, and said post-amp filter cause distortion to the information signal in a sequence of linear, non-linear, and linear.
3. A system claimed in claim 1, wherein said corrector is located upstream of said filter means and said amplifier means.
4. A digital broadcast transmission system comprising signal provision means for providing an electrical information-conveying signal along a signal stream, antenna means, located at the end of the signal stream, for emitting a broadcast signal that conveys the contents of the information signal, a plurality of components located along the signal stream between said signal provision means and said antenna means, said plurality of components causing distortion to the information signal, at least one of said plurality of components causing linear distortion to the information signal and at least one of said plurality of components causing non-linear distortion to the information signal, and a single corrector for pre-distorting the information signal to compensate for all of the distortion caused by said plurality of components.
5. A system as claimed in claim 4, wherein said single corrector is a volterra filter, and in which said plurality of components includes an amplifier, a pre-amp filter located upstream of said amplifier, and a post-amp filter located downstream of said amplifier, said pre-amp filter, said amplifier, and said post-amp filter cause distortion to the information signal in a sequence of linear, non-linear, and linear.
6. A system as claimed in claim 4, wherein said corrector is located upstream of said pre-amp filter, said amplifier, and said post-amp filter.




7. A system as claimed in claim 4, including another component located along the signal stream between said signal provision means and said antenna means, said other component causing linear distortion to the information signal, and another corrector for pre-distorting the information signal to compensate for the distortion caused by said other component, and said other component includes a high-power filter.

8. A method of transmitting a broadcast signal from a digital transmitter, said method comprising providing an information signal in digital format, converting the information signal to analog format, amplifying the analog information signal, said step of amplifying includes causing non-linear distortion to the information signal, filtering the analog information signal prior to said step of amplifying, said step of filtering prior to amplifying includes causing linear distortion to the information signal, filtering the analog information signal after said step of amplifying, said step of filtering after amplifying includes causing linear distortion to the information signal, and correcting the linear and non-linear distortion in a single corrector.

9. A method as claimed in claim 8 wherein said step of correction includes determining a pre-distortion to be imposed onto the information signal.

10. A method as claimed in claim 8, wherein said step of determining a pre-distortion includes initially abstaining from imposing a pre-distortion onto the information signal and determining distortion caused by said steps of amplifying and filtering.

1/3



2/3




FIG. 3




FIG. 4

3/3




FIG. 6

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/US 00/13130

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H03F1/32

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H03F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X A	EP 0 121 446 A (THOMSON CSF) 10 October 1984 (1984-10-10) the whole document	1,3,4,6, 8-10 7
X A	US 5 486 789 A (OPAS GEORGE F ET AL) 23 January 1996 (1996-01-23) the whole document	1-6,8-10 7
A	US 4 870 371 A (GOTTWALD ALFONS ET AL) 26 September 1989 (1989-09-26)	
A	US 5 900 778 A (MOURA JOSEM F ET AL) 4 May 1999 (1999-05-04)	

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

Z document member of the same patent family

Date of the actual completion of the international search

4 September 2000

Date of mailing of the international search report

11/09/2000

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3018

Authorized officer

Segaert, P

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 00/13130

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0121446 A	10-10-1984	FR 2541058 A	17-08-1984
		CA 1208709 A	29-07-1986
		DE 3463992 D	02-07-1987
		JP 59158113 A	07-09-1984
US 5486789 A	23-01-1996	EP 0758501 A	19-02-1997
		FI 964290 A	25-10-1996
		JP 9512692 T	16-12-1997
		WO 9627236 A	06-09-1996
US 4870371 A	26-09-1989	DE 3614785 A	21-01-1988
		DE 3773253 A	31-10-1991
		EP 0243898 A	04-11-1987
US 5900778 A	04-05-1999	NONE	

10/10/2011

THIS PAGE BLANK (USPTO)